

Honeywell

907

620 LCS and S9000 Fuse and Battery Replacement

MODEL NUMBER	FUSE TYPE	620 FUSE MODEL NO.	MANUFACTURER'S NAME AND PART NUMBER
620-0036 P/S (230VAC)	1 Amp Slo-Blo 5 x 20 mm (250V)	629-1002	SAN-O SD6-1A, LITTELFUSE 239001, BUSSMAN GMC-1
620-0036 P/S (115VAC) 620-0083 P/S (230VAC) 621-9933C P/S (230VAC)	2 Amp Slo-Blo 5 x 20 mm	629-1003	SAN-O SD6-2A, LITTELFUSE 239002, BUSSMAN GMC-2
621-2100RC AC Output 621-2102RC AC Output 621-2150RC AC Output	3 Amp Slo-Blo Subminiature	629-1022	LITTELFUSE 473003, BEL MS3
621-2101RC AC Output	3 Amp Slo-Blo 5 x 20 mm (250V)	629-1023	LITTELFUSE 239003, BEL 5TT3
621-2200RC AC Output* 621-2201RC AC Output 621-2500RC AC Output* 621-6700RC DC Output*	3 Amp Fast-Blo 5 x 20 mm (250V)	629-1006	SAN-O 4MT-3A, BEL 5MF3, LITTELFUSE 235003, BUSSMAN GMC-3
620-0046 P/S (24VDC) 621-6500RC DC Output 621-6600RC DC Output 621-6701RC DC Output 621-9932 P/S (24VDC)	8 Amp Fast-Blo 5 x 20 mm (250V)	629-1007	LITTELFUSE 216008, BUSSMAN GDB-8
621-6575RC DC Output	10 Amp Fast-Blo Subminiature	629-1008	SAN-O SP5-10, LITTELFUSE 255010 or 251010, BUSSMAN A10 or AC10, WICKMANN 19275-10.0A
620-0041 P/S (230VAC) 621-6300RC DC Output 621-9934C P/S (230VAC)	0.8 Amp Slo-Blo 5 x 20 mm	629-1009	SAN-O SD6-800MA, BEL 5MT800MA, LITTELFUSE 239.800, BUSSMAN GMC-0.8
621-2200RC AC Output* 621-2500RC AC Output* 621-2550RC AC Output 621-6502R DC Output** 621-6551RC DC Output 621-6700RC DC Output*	3 Amp Fast-Blo Subminiature	629-1012	SAN-O SP5-3, LITTELFUSE 255003 or 251003, BUSSMAN A3 or AC3, WICKMANN 19275-3.0A

* Fuse type depends on product release date.
(Current models use fuse 629-1012.)

** More than one fuse is installed.

Honeywell

620 LCS and S9000 Fuse and Battery Replacement

MODEL NUMBER	FUSE TYPE	620 FUSE MODEL NO.	MANUFACTURER'S NAME AND PART NUMBER
621-0018RC Ab. Encdr** 621-6450RC DC Output 621-6502R DC Output** 621-6550RC DC Output 621-6650RC DC Output	7 Amp Fast -Blo Subminiature	629-1016	SAN-O SP5-7, LITTELFUSE 255077 or 251007, BUSSMAN A7 or AC7, WICKMANN 19275-7.0A
620-0083 P/S (115VAC) 621-9933C P/S (115VAC)	4 Amp Slo-Blo 5 x 20 mm	629-1017	SAN-O SD6-4A, BEL 5MT4, LITTELFUSE 239004
620-0041 P/S (115VAC) 621-9934C P/S (115VAC)	1.6A Slo-Blo 20mm	629-1018	BUSSMAN GDC-1.6, LITTELFUSE 21801.6
620-0047 P/S (24VDC)	6.3 Amp Slo-Blo 5 x 20 mm	629-1019	SCHURTER 034.3125, SAN-O ET 6.3
621-2175RC AC Output 621-0018RC Ab. Encdr**	5 Amp Fast-Blo Subminiature	629-1020	WICKMANN 1975-5.0A, SAN-O SP5-5, LITTELFUSE 255005 OR 251005, BUSSMAN A5 OR AC5

** More than one fuse is installed.

620-LCS and S9000 Battery Requirements

Product Model Number	Battery Model Number	Battery Type
620-12/-1633/-3632 Logic Controller 620-11/-14/-1631 Logic Controller 9010-012/-016/-036 Logic Controller	629-3000	Size C Lithium 3.5 Vdc
620-25/35 -20/30 Logic Controller S9100 and S9200 Controllers	629-3001	Size D Lithium 3.4 Vdc
620-06/-10/-15 Logic Controller 9010-015 Logic Controller 620-0073C ELPM 620-0089 EIM 627-1002/1003RC Minicop module	629-3002	Size AA Lithium 3.4 Vdc
621-0012RC ASCII module 621-0016 CAM module	629-3003	Size 1/2 AA Lithium 3.4 Vdc.
620-0071 LMM 620-0072 LPM	629-3004	Size 2/3 AA Lithium 3.4 Vdc