



UDC 2500 Application Note

Restoring Factory Configuration

Introduction


This procedure restores the configuration of the instrument back to the Factory Settings.

ATTENTION: Restoring the factory configuration overwrites all user-entered configuration changes.

**This procedure cannot be undone.
It is a one-way process.**

Table 1 explains how to restore Factory Configuration.

Table 1 Restoring Factory Configuration

Step	What to do
1	Turn off the power to the instrument for at least five seconds.
2	Turn the power back on and simultaneously press the “FUNCTION” and  keys. This must be done while “TEST DONE” is being displayed.
3	If step 2 was performed correctly, the instrument will now display “UDC” [Upper] “UPDATE” [Lower].
4	Press the Function Key. The instrument will now display “CFG” “RESTORE”
5	Press the Function Key. The instrument will now display “DOIN” “RESTORE”
6	When the instrument finishes the restore operation, it automatically resets itself and restarts in the product mode. The instrument configuration will now be the same as it was when the instrument left the factory and all user-entered configurations since that time have been overwritten.