

3.9 Input 2 Set Up Group

Function Prompts

Table 3-8 INPUT2 Group (Numeric Code 700) Function Prompts

Prompt		Description	Selection or Range of Setting		Factory Setting																																																								
English	Numeric Code		Numeric Code	English																																																									
IN2TYP	701	Input 2 Type	0	DIS	1-5V																																																								
			25	0-20 (mA)																																																									
			26	4-20 (mA)																																																									
			29	0-5 (Volts)																																																									
			30	1-5 (Volts)																																																									
			34	0-2 (Volts)																																																									
XMITR2	702	Transmitter Characterization for Input 2	<table border="1"> <thead> <tr> <th>Numeric</th> <th>English</th> <th>Numeric</th> <th>English</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>B</td> <td>13</td> <td>S</td> </tr> <tr> <td>1</td> <td>E H</td> <td>14</td> <td>T H</td> </tr> <tr> <td>2</td> <td>E L</td> <td>15</td> <td>T L</td> </tr> <tr> <td>3</td> <td>J H</td> <td>16</td> <td>W H</td> </tr> <tr> <td>4</td> <td>J L</td> <td>17</td> <td>W L</td> </tr> <tr> <td>5</td> <td>K H</td> <td>18</td> <td>100H</td> </tr> <tr> <td>6</td> <td>K L</td> <td>19</td> <td>100L</td> </tr> <tr> <td>7</td> <td>NNMH</td> <td>20</td> <td>200</td> </tr> <tr> <td>8</td> <td>NNML</td> <td>21</td> <td>500</td> </tr> <tr> <td>9</td> <td>N90H</td> <td>22</td> <td>RADH</td> </tr> <tr> <td>10</td> <td>N90L</td> <td>23</td> <td>RADI</td> </tr> <tr> <td>11</td> <td>NIC</td> <td>24</td> <td>LIN</td> </tr> <tr> <td>12</td> <td>R</td> <td>25</td> <td>SrT</td> </tr> </tbody> </table>		Numeric	English	Numeric	English	0	B	13	S	1	E H	14	T H	2	E L	15	T L	3	J H	16	W H	4	J L	17	W L	5	K H	18	100H	6	K L	19	100L	7	NNMH	20	200	8	NNML	21	500	9	N90H	22	RADH	10	N90L	23	RADI	11	NIC	24	LIN	12	R	25	SrT	LIN
			Numeric	English	Numeric	English																																																							
			0	B	13	S																																																							
			1	E H	14	T H																																																							
			2	E L	15	T L																																																							
			3	J H	16	W H																																																							
			4	J L	17	W L																																																							
			5	K H	18	100H																																																							
			6	K L	19	100L																																																							
			7	NNMH	20	200																																																							
			8	NNML	21	500																																																							
			9	N90H	22	RADH																																																							
			10	N90L	23	RADI																																																							
11	NIC	24	LIN																																																										
12	R	25	SrT																																																										
<table border="1"> <thead> <tr> <th>Numeric Code</th> <th>English</th> </tr> </thead> </table>		Numeric Code	English																																																										
Numeric Code	English																																																												
IN2 HI	703	Input 2 High Range Value	-999 to 9999 floating in engineering units	2400																																																									
IN2 LO	704	Input 2 Low Range Value	-999 to 9999 floating in engineering units	0																																																									
RATIO2	705	Ratio on Input 2	-20.0 to 20.0	1.00																																																									
BIAS 2	706	Bias on Input 2	-999 to 9999	0.0																																																									
FILTR2	707	Filter for Input 2	0 to 120 seconds 0 = No Filter	1.0																																																									